

DESCRIPTION

CHOLESTERIC LIQUID CRYSTAL DRIVING DEVICE AND DRIVING METHOD

5 Technical Field

The present invention relates to cholesteric liquid crystal driving devices and cholesteric liquid crystal driving methods.

10 Background Art

A plurality of cholesteric liquid crystals is used for known cholesteric liquid crystal driving devices. The plurality of cholesteric liquid crystals is provided at intersections of a plurality of scanning lines (gate lines) and a plurality of data lines (source lines). Also, the voltage between the corresponding scanning lines and the corresponding data lines defines the screw axis of corresponding liquid crystal molecules in a P-orientation, an F-orientation, or an H-orientation.

20 Known cholesteric liquid crystal driving devices display images by selectively reflecting or transmitting light in accordance with the orientation. A liquid crystal driving method described in United States Patent Application No. 5,748,277 is known.

25 However, since known cholesteric liquid crystal driving devices display the images, irrespective of the content of the images, by driving the cholesteric liquid crystals in accordance with a cycle including three periods, a reset

period for resetting the cholesteric liquid crystals, a selection period for selecting the cholesteric liquid crystals in a desired orientation, and a holding period for holding the cholesteric liquid crystals in the desired orientation, the
5 images cannot be displayed at high speed.

Disclosure of Invention

Cholesteric liquid crystal driving according to the present invention includes a detection function for detecting
10 a first scanning line and a second scanning line, wherein, in image data having two or more gray levels to be displayed by a plurality of cholesteric liquid crystals provided at intersections of a plurality of scanning lines and a plurality of data lines, the orientation of each of the plurality of
15 cholesteric liquid crystals being defined in a P-orientation, an F-orientation, or an H-orientation in accordance with a voltage between the corresponding scanning lines and the corresponding data lines, one part of the image data
20 corresponding to a cholesteric liquid crystal on the first scanning line has different gray levels other than a halftone and another part of the image data corresponding to a cholesteric liquid crystal on the second scanning line has the same gray level other than the halftone; a first driving function for displaying, on the basis of a detection result
25 for the first scanning line by the detection function, the one part of the image data to be displayed by the cholesteric liquid crystal on the first scanning line by driving the cholesteric liquid crystal on the first scanning line in

accordance with a first cycle including a reset period for resetting the cholesteric liquid crystal in the H-orientation, a selection period for selecting the cholesteric liquid crystal, which is reset in the H-orientation, in a TP

5 orientation, and a holding period for holding the cholesteric liquid crystal, which is selected in the TP orientation, in the F-orientation and in accordance with a second cycle including a reset period for resetting the cholesteric liquid crystal in the H-orientation, a selection period for selecting

10 the cholesteric liquid crystal, which is reset in the H-orientation, in the H-orientation, and a holding period for holding the cholesteric liquid crystal, which is selected in the H-orientation, in the F-orientation; and a second driving function for displaying, on the basis of a detection result

15 for the second scanning line by the detection function, the other part of the image data to be displayed by the cholesteric liquid crystal on the second scanning line by driving the cholesteric liquid crystal on the second scanning line in accordance with a third cycle including a reset period

20 for resetting the cholesteric liquid crystal in the H-orientation and a holding period for holding the cholesteric liquid crystal, which is reset in the H-orientation, in the F-orientation or in accordance with a fourth cycle including a reset period for resetting the cholesteric liquid crystal in

25 the H-orientation, the cholesteric liquid crystal, which is reset in the H-orientation, being transit to the TP orientation at the end of the reset period.

According to the cholesteric liquid crystal driving of the

present invention, the first driving function drives the
cholesteric liquid crystal on the first scanning line detected
by the detection function in accordance with the first or
second cycle, which corresponds to the known cycle, and the
5 second driving function drives the cholesteric liquid crystal
on the second scanning line detected by the detection function
in accordance with the third or fourth cycle, which is shorter
than the first and second cycles. Thus, the image can be
displayed at a speed higher than a case where cholesteric
10 liquid crystals are driven in accordance with the known cycle.

In the cholesteric liquid crystal driving according to the
present invention, the detection function detects at least one
scanning line group including two or more scanning lines, each
of the scanning lines corresponding to the second scanning
15 line, and the second driving function performs first
synchronous driving for synchronously driving the two or more
scanning lines included in the one scanning line group in
accordance with the third cycle or the fourth cycle or
performs first asynchronous driving for asynchronously driving
20 the two or more scanning lines included in the one scanning
line group in accordance with the third cycle or the fourth
cycle.

In the cholesteric liquid crystal driving according to the
present invention, the second driving function performs second
25 synchronous driving for synchronously driving the two or more
scanning lines included in another scanning line group in
accordance with the third cycle or the fourth cycle so as to
be in synchronization with the first synchronous driving or in

asynchronization with the first synchronous driving.

In the cholesteric liquid crystal driving according to the present invention, the second driving function performs second asynchronous driving for asynchronously driving the two or more scanning lines included in another scanning line group in accordance with the third cycle or the fourth cycle so as to be in synchronization with the first asynchronous driving or in asynchronization with the first asynchronous driving.

10 Brief Description of the Drawings

The above-mentioned and other objects, features, and advantages of the present invention will become apparent more easily from the following description of preferred embodiments of the present invention with reference to the attached drawings.

Fig. 1 is a block diagram showing the structure of an exemplary cholesteric liquid crystal driving device.

Fig. 2 illustrates an image displayed by the exemplary cholesteric liquid crystal driving device.

20 Fig. 3 includes sectional views each showing an orientation of a pixel.

Fig. 4 is a graph showing the relationship between the voltage applied to a cholesteric liquid crystal and the type of orientation (the reflectance).

25 Fig. 5 includes time charts each showing a driving operation of a cholesteric liquid crystal by a character line driving method.

Fig. 6 includes time charts each showing a driving

operation of a cholesteric liquid crystal by a space between lines driving method.

Fig. 7 is a time chart showing a driving operation by a character line driving method using a pipeline system.

5 Fig. 8 is a time chart showing a driving operation of the exemplary cholesteric liquid crystal driving device.

Fig. 9 is a time chart showing another driving operation of the exemplary cholesteric liquid crystal driving device.

10 Fig. 10 is a time chart showing another driving operation of the exemplary cholesteric liquid crystal driving device.

Best Mode for Carrying Out the Invention

15 A cholesteric liquid crystal driving device according to the present invention will be described with reference to embodiments.

[Embodiments]

Fig. 1 is a block diagram showing the structure of an exemplary cholesteric liquid crystal driving device. Fig. 2 illustrates an image displayed by the exemplary cholesteric liquid crystal driving device.

25 An exemplary cholesteric liquid crystal driving device 1 (hereinafter, referred to as a "driving device 1") includes a cholesteric liquid crystal display medium 2, a frame memory 3, a space between lines analyzer 4, a scan controller 5, a source driver 6, and a gate driver 7, as shown in Fig. 1, so that an image 8, such as an instruction manual composed of character lines and spaces between lines (including margins),

having two or more gray levels, as shown in Fig. 2, can be displayed.

The cholesteric liquid crystal display medium 2 includes a plurality of pixels P11 to Pmn provided at intersections of corresponding data lines (source lines) X1 to Xm and corresponding scanning lines (gate lines) Y1 to Yn.

Fig. 3 includes sectional views each showing an orientation of a pixel. As is known, each of the pixels P11 to Pmn includes a transparent electrode 2a, a cholesteric liquid crystal 2b, a transparent electrode 2c, and a black light-absorption layer 2d, as shown in Fig. 3. Each of the pixels P11 to Pmn selectively reflects or transmits light of a particular wavelength in accordance with a spiral pitch of a molecule of the cholesteric liquid crystal 2b, in other words, in accordance with the orientation.

The cholesteric liquid crystal 2b can be changed between a planar orientation (hereinafter, referred to as a "P-orientation") shown in Fig. 3(A), a focal conic orientation (hereinafter, referred to as an "F-orientation") shown in Fig. 3(B), and a homeotropic orientation (hereinafter, referred to as an "H-orientation") shown in Fig. 3(C). In the P-orientation shown in Fig. 3(A), the cholesteric liquid crystal 2b displays "white" in accordance with a selected reflection function. In the F-orientation shown in Fig. 3(B) and the H-orientation shown in Fig. 3(C), the cholesteric liquid crystal 2b displays "black" of the light-absorption layer 2d in accordance with a selected transmission function.

Since the P-orientation and the F-orientation are stable,

the P-orientation and the F-orientation are maintained after a voltage is not applied to the cholesteric liquid crystal 2b. The cholesteric liquid crystal 2b in the H-orientation is transit to the P-orientation (hereinafter, referred to as

5 "transient planar transition (TP orientation)" due to a sudden reduction in the applied voltage. After the transient planar transition (TP orientation), the cholesteric liquid crystal 2b is transit to the F-orientation by moderately reducing the applied voltage.

10 Fig. 4 is a graph showing the relationship between a voltage applied to a cholesteric liquid crystal and the type of orientation (the reflectance). When the initial orientation of the cholesteric liquid crystal 2b (the orientation after a voltage-applied state is changed to a non-

15 voltage-applied state) is the P-orientation, if the applied voltage is from V_0 to less than V_1 , the cholesteric liquid crystal 2b is in the P-orientation. If the applied voltage is from V_1 to less than V_2 , the cholesteric liquid crystal 2b is transit from the P-orientation to the F-orientation. If the

20 applied voltage is from V_2 to less than V_3 , the cholesteric liquid crystal 2b is in the F-orientation. If the applied voltage is V_3 or more, the cholesteric liquid crystal 2b is in the H-orientation. In contrast, when the initial orientation of the cholesteric liquid crystal 2b is in the P-orientation,

25 if the applied voltage is from V_0 to less than V_2 , the cholesteric liquid crystal 2b is in the P-orientation. If the applied voltage is V_3 or more, the cholesteric liquid crystal 2b is in the H-orientation.

Referring back to Fig. 1, the frame memory 3 stores the image 8, shown in Fig. 2, to be displayed by the cholesteric liquid crystal display medium 2 using known line-sequential driving.

5 The space between lines analyzer 4, which is a detection circuit, analyzes whether an image part of the image 8, stored in the frame memory 3, to be scanned with the gate lines Y1 to Yn is a character line or a space between lines, in other words, whether the image part has different gray levels, each
10 of the gray levels being other than a halftone (that is, each of the gray levels being white or black) or has the same gray level other than the halftone. More specifically, for example, if an image part to be displayed by the pixels 11 to Pm1 on the gate line Y1 has both "white" and "black", the space
15 between lines analyzer 4 determines that the gate line Y1 is a "character line". In contrast, if the image part has "white" or "black", the space between lines analyzer 4 determines that the gate line Y1 is a "space between lines".

 The scan controller 5, which includes a first driving
20 circuit and a second driving circuit, causes the gate driver 7 to drive the gate lines Y1 to Ym in accordance with a character line driving method (Fig. 5) or a space between lines driving method (Fig. 6), which will be described below, on the basis of analysis results for the image 8 by the space
25 between lines analyzer 4.

 The source driver 6 applies data voltages corresponding to the image 8 stored in the frame memory 3 to the source lines X1 to Xm. The gate driver 7 applies gate voltages to the gate

lines Y1 to Yn, under the control of the scan controller 5.

Fig. 5 includes time charts showing a driving operation of a cholesteric liquid crystal according to the character line driving method. According to the character line driving method, as shown in Figs. 5(A) and (B), for example, in a cycle including three periods, a reset period T_r , a selection period T_s , and a holding period T_h , by changing a voltage applied to the pixels P11 to Pm1 on the gate line Y1 every period, the orientation of the cholesteric liquid crystal 2b of each of the pixels P11 to Pm1 is changed.

More specifically, in order to display "black" by setting the cholesteric liquid crystal 2b in the F-orientation, the cholesteric liquid crystal 2b is set in the H-orientation by applying a reset voltage (V_3 or more) during the reset period T_r , the cholesteric liquid crystal 2b is set in the TP-orientation by applying a selection voltage (from V_1 to less than V_2) during the selection period T_s , and the cholesteric liquid crystal 2b is set in the F-orientation by applying a holding voltage (from V_2 to less than V_3) during the holding period T_h , as shown in Fig. 5(A). Accordingly, the cholesteric liquid crystal 2b is maintained in an F-orientation state, that is, a "black" state after the holding period T_h . In contrast, in order to display "white" by setting the cholesteric liquid crystal 2b in the P-orientation, the cholesteric liquid crystal 2b is set in the H-orientation by applying a reset voltage (V_3 or more) during the reset period T_r , the cholesteric liquid crystal 2b is kept in the H-orientation by applying a selection voltage (V_3 or more)

during the selection period T_s , and the cholesteric liquid crystal 2b is kept in the H-orientation by applying a voltage (V_3 or more) during the holding period T_h , as shown in Fig. 5(B). Accordingly, the cholesteric liquid crystal 2b is maintained in a P-orientation state, that is, a "white" state after the holding period T_h .

Fig. 6 includes time charts showing a driving operation of a cholesteric liquid crystal according to the space between lines driving method. According to the space between lines driving method, as shown in Fig. 6(A), for example, in a cycle including two periods, a reset period T_r and a holding period T_h , by changing a voltage applied to the pixels P11 to Pm1 on the gate line Y1 every period, the orientation of the cholesteric liquid crystal 2b of each of the pixels P11 to Pm1 is changed. Also, as shown in Fig. 6(B), for example, in a cycle including only a reset period T_r , by changing a voltage applied to the pixels P11 to Pm1 on the gate line Y1, the orientation of the cholesteric liquid crystal 2b of each of the pixels P11 to Pm1 is changed.

More specifically, in the space between lines driving method, in order to display "black" by setting the cholesteric liquid crystal 2b in the F-orientation, the cholesteric liquid crystal 2b is set in the H-orientation by applying a reset voltage (V_3 or more) during the reset period T_r , and the cholesteric liquid crystal 2b is set in the F-orientation by applying a holding voltage (from V_2 to less than V_3) during the holding period T_h , as shown in Fig. 6(A). Accordingly, the cholesteric liquid crystal 2b is maintained in an F-

orientation state, that is, a "black" state after the holding period T_h . In contrast, in order to display "white" by setting the cholesteric liquid crystal 2b in the P-orientation, the cholesteric liquid crystal 2b is set in the H-orientation by applying a reset voltage (V_3 or more) during the reset period T_r , and after the reset period T_r , the cholesteric liquid crystal 2b is transit to the P-orientation via a TP orientation, as shown in Fig. 6(B). Accordingly, the cholesteric liquid crystal 2b is maintained in a P-orientation state, that is, a "white" state.

In the character line driving method, due to line-sequential driving, in other words, for example, in order that a selection period T_s for the pixels P_{11} to P_{m1} on the gate line Y_1 does not overlap with a selection period T_s for the pixels P_{12} to P_{m2} on the gate line Y_2 , the pipeline system is adopted.

Fig. 7 is a time chart showing a driving operation by the character line driving method using the pipeline system. In the character line driving method using the pipeline system, in order that selection periods T_s in which selection voltages V_s are applied do not overlap with each other between the gate lines Y_1 to Y_n , corresponding cycles are allocated to the gate lines Y_1 to Y_n . For example, a selection period T_{s1} for the gate line Y_1 to display a character line CH_1 , which is a part of the image 8, a selection period T_{s2} for the gate line Y_2 to display a space between line BL_1 , which is another part of the image 8, and a selection period T_{s3} for the gate line Y_3 to display a space between lines BL_2 , which is another part of

the image 8, are arranged so as not to overlap with each other.

As described above, the driving device 1 adopts the character line driving method shown in Fig. 5 using the pipeline system shown in Fig. 7 and adopts the space between lines driving method shown in Fig. 6. The operation of the driving device 1 is described next.

Fig. 8 is a time chart showing a driving operation of the exemplary cholesteric liquid crystal driving device. The driving operation of the driving device 1 will be described with reference to Fig. 8. In order to facilitate explanations and understanding, for the image 8 shown in Fig. 2, it is assumed that characters and spaces between lines are regarded as "black" and "white", respectively, and that voltages applied to the pixels P11 to Pmn shown in Fig. 1 are defined only by gate voltages applied to the gate lines Y1 to Yn.

The space between lines analyzer 4 analyzes whether an image part corresponding to each of the gate lines Y1 to Yn of the image 8, stored in the frame memory 3, is a character line or a space between lines. Accordingly, the space between lines analyzer 4 finds, for example, that an image part to be displayed by the gate line Y1 is a character line CH1, image parts to be displayed by the gate lines Y2 to Y4, which constitute a scanning line group, are spaces between lines BL1 to BL3, and an image part to be displayed by the gate line Y5 is a character line CH2.

Furthermore, the space between lines analyzer 4 instructs the scan controller 5 to drive the gate line Y1, which is to display the character line CH1, in the character line driving

method using the pipeline system, to drive the gate lines Y2 to Y4, which are to display the spaces between lines BL1 to BL3, in the space between lines driving method, and to drive the gate line Y5, which is to display the character line CH2, in the character line driving method using the pipeline system. The space between lines analyzer 4 also instructs the scan controller 5 to drive each of the gate lines Y6 to Yn in the character line driving method using the pipeline system or the space between lines driving method depending on whether each image part is a character line or a space between lines.

After receiving the instructions from the space between lines analyzer 4, the scan controller 5 causes the gate driver 7 to drive the gate line Y1 in the character line driving method using the pipeline system, to drive the gate lines Y2 to Y4 in the space between lines driving method, and to drive the gate line Y5 in the character line driving method using the pipeline system. The scan controller 5 also causes the gate driver 7 to drive each of the gate lines Y6 to Yn in the character line driving method using the pipeline system or the space between lines driving method.

More specifically, the gate driver 7 applies to the pixels P11 to Pm1 on the gate line Y1 a reset voltage Vr during a reset period Tr from a time t0 to a time t4, a selection voltage Vs during a selection period Ts from the time t4 to a time t6, and a holding voltage Vh during a holding period Th from the time t6 to a time t10. The gate driver 7 also applies to the pixels P12 to Pm2, P13 to Pm3, and P14 to Pm4 on the gate lines Y2 to Y4, which constitute a scanning line

group, a reset voltage V_r during a reset period T_r from the time t_0 to the time t_4 . Similarly, the gate driver 7 applies voltages to pixels on the gate lines Y_7 to Y_9 , which constitute a scanning line group, and to pixels on the gate lines Y_{12} to Y_{14} , which constitute a scanning line group. Furthermore, the gate driver 7 applies to the pixels P_{15} to P_{m5} on the gate line Y_5 a reset voltage V_r during a reset period T_r from the time t_1 to the time t_6 , a selection voltage V_s during a selection period T_s from the time t_6 to the time t_8 , and a holding voltage V_h during a holding period T_h from the time t_8 to the time t_{12} .

In other words, (1) at the time t_0 , the gate driver 7 starts application of a reset voltage V_r to the gate line Y_1 for the reset period T_r in the character line driving method using the pipeline system and application of a reset voltage V_r to the gate lines Y_2 to Y_4 for the reset period T_r in the space between lines driving method. (2) At the time t_1 , the gate driver 7 starts application of a reset voltage V_r to the gate line Y_5 for the reset period T_r in the character line driving method using the pipeline system. (3) At the time t_4 , the gate driver 7 starts application of a selection voltage V_s to the gate line Y_1 for the selection period T_s in the character line driving method using the pipeline system and ends the application of the reset voltage V_r to the gate lines Y_2 to Y_4 for the reset period T_r in the space between lines driving method. (4) At the time t_6 , the gate driver 7 starts application of a holding voltage V_h to the gate line Y_1 for the holding period T_h in the character line driving method

using the pipeline system and application of a selection voltage V_s to the gate line Y5 for the selection period T_s in the character line driving method using the pipeline system.

(5) At the time t_8 , the gate driver 7 starts application of a holding voltage V_h to the gate line Y5 for the holding period T_h in the character line driving method using the pipeline system. (6) At the time t_{10} , the gate driver 7 ends the application of the holding voltage V_h to the gate line Y1 for the holding period T_h in the character line driving method using the pipeline system. (7) At the time t_{12} , the gate driver 7 ends the application of the holding voltage V_h to the gate line Y5 for the holding period T_h in the character line driving method using the pipeline system.

As described above, in the driving device 1, the space between lines analyzer 4 analyzes whether an image part corresponding to each of the gate lines Y1 to Yn of the image 8, stored in the frame memory 3, is a character line or a space between lines, and the scan controller 5 drives gate lines to display character lines in the character line driving method using the pipeline system and drives gate lines to display spaces between lines in the space between lines driving method in accordance with analysis results by the space between lines analyzer 4. The space between lines driving method is completed in a time shorter than the character line driving method. Thus, a time required for driving all the gate lines Y1 to Yn can be reduced compared with known cholesteric liquid crystal driving devices in which all the gate lines Y1 to Yn are driven in the character line

driving method. In other words, the image 8 can be displayed at a speed higher than a case where a known driving device is used.

Fig. 9 is a time chart showing another driving operation of the exemplary cholesteric liquid crystal driving device. According to the driving operation shown in Fig. 8, the cycle for driving the gate lines Y2 to Y4, which constitute a scanning line group for the spaces between lines BL1, BL2, and BL3, the cycle for driving the gate lines Y7 to Y9, which constitute a scanning line group for the spaces between lines BL4 to BL6, and the cycle for driving the gate lines Y12 to Y14, which constitute a scanning line group for the spaces between lines BL7 to BL9, are equal to each other, the spaces between lines BL1 to BL9 being parts of the image 8 shown in Fig. 2. In other words, according to the driving operation shown in Fig. 8, the cycles are synchronized with each other. However, according to the driving operation shown in Fig. 9, the cycle for driving the gate lines Y2 to Y4, the cycle for driving the gate lines Y7 to Y9, and the cycle for driving the gate lines Y12 to Y14 are shifted by the length of a selection period T_s . In other words, according to the driving operation shown in Fig. 9, driven asynchronously with each other. Accordingly, compared with the driving operation shown in Fig. 8 in which the gate lines Y2 to Y4, the gate lines Y7 to Y9, and the gate lines Y12 to Y14 are driven at the same time, fringe patterns, formed by a plurality of lines parallel to the X-direction, generated by driving the gate lines Y2 to Y4, Y7 to Y9, and Y12 to Y14 are prevented from being clear.

Fig. 10 is a time chart showing another driving operation of the exemplary cholesteric liquid crystal driving device. For example, according to the driving operation shown in Fig. 9, the three gate lines Y2, Y3, and Y4, which constitute a scanning line group, the gate lines are driving at the same time, in other words, the three gate lines Y2, Y3, and Y4 are driven synchronously with each other. However, according to the driving operation shown in Fig. 10, in the driving device 1, the three gate lines Y2, Y3, and Y4 are driven so as to be shifted by the length of a selection period T_s , in other words, the three gate lines Y2, Y3, and Y4 are driven asynchronously with each other. Accordingly, compared with the driving operation shown in Fig. 9 in which the gate lines Y2 to Y4 are driven synchronously with each other, the fringe patterns are further prevented from being clear.